

FAQ: How to Configure the DCS-933L to Send E-mail Snapshots on Gmail Account

Release date: 15/10/2013

Model Support: DCS-933L

H/W: A1

S/W: 1.00



การตั้งค่าบน DCS-933L เพื่อส่งภาพ ไปยัง Gmail Account สามารถทำได้อย่างไร

ขั้นตอนที่ 1: เรียกใช้งาน โปรแกรม CD Setup ที่มาพร้อมกับ DCS-933L บนหน้าจอของ Setup Wizard คลิ๊กบนปุ่ม Setup your Cloud Camera



ขั้นตอนที่ 2: คลิ๊กบนปุ่ม Start เพื่อไปยังขั้นตอนต่อไป

🖸 mydlink Setup Wizard		
mydlink	DC	S-933L Setup Wizard
Welcome You will be able to set up your Cloud Camera	0	
to use mydlink Cloud service, or you can choose to have the camera run independently.)
Select your language:	00	
Start		
Troubleshooting Downloads	About	Exit

ขั้นตอนที่ 3: ภายใต้ End User License Agreement ทำเครื่องหมายเพื่อเลือกบน I accept these Terms and Conditions แล้วคลิ๊กบนปุ่ม Next



้ ขั้นตอนที่ 4: เสียบสายแลนที่พอร์ตด้านหลังของกล้อง แล้วคลิ๊กปุ่ม Next เพื่อไปยังขั้นตอนต่อไป



ขั้นตอนที่ 5: เสียบสายแลนอีกค้านหนึ่งเข้ากับพอร์ตแลนของเราเตอร์ แล้วกคปุ่ม Next



ขั้นตอนที่ 6: เชื่อมอะแคปเตอร์ไปยังช่องเสียบไฟที่อยู่ด้านหลังของ DCS-933L แล้วเสียบอะแคป เตอร์เข้ากับปลั๊กไฟ แล้วคลิ๊กปุ่ม Next



ขั้นตอนที่ 7: ไฟ LED ของกล้องจะเปลี่ยนเป็นสีเขียวเมื่อพร้อมใช้งาน กคปุ่ม Next



ขั้นตอนที่ 8: คลิ๊กบนปุ่ม Yes ถ้า LED ที่อยู่ค้านหลังเปลี่ยนเป็นสีเขียว



ขั้นตอนที่ 9: คุณจะเห็นข้อมูลเกี่ยวกับอุปกรณ์กล้องของคุณ ซึ่งประกอบด้วยหมายเลข IP และ MAC Address โดยคุณสามารถพิมพ์รหัสผ่าน แล้วกดปุ่ม Next

elec	t your Cloud	I Camera	Connect 1	Network 🕝	Enable 🧲
	Cloud Camera	MAC ID 7	IP address	Connection	n
	Searching Close	ud Cameras			
Re	Searching Clou segistered with mydlink	ud Cameras	tered 💁 Wi	red 👰	Wireless
E Re	Searching Clou egistered with mydlink	ud Cameras Notregist	tered 9 r wi Please enter a	red 👰 🖓	Wireless Ire your camera
an't find	Searching Clou egistered with mydlink t your Cloud Camera in the	ud Cameras Not regist	tered Please enter a Please enter a Admin account: ac Password: P	red 👷 🖓	Wireless ire your camera

้ขั้นตอนที่ 10: เปิดเวบบราวเซอร์ โดยให้พิมพ์หมายเลขไอพีของกล้องที่ช่อง Address แล้วล็อคอิน โดยพิมพ์บัญชีผู้ใช้งานเป็น admin และรหัสผ่านของกล้องของคุณ แล้วกดปุ่ม Log In

http://192.168.0.100

Windows Secur	ity	×
The server 19	2.168.0.100 at DCS-933L requires a username ar	nd password.
Warning: Thi sent in an ins connection).	s server is requesting that your username and p ecure manner (basic authentication without a s	assword be secure
	admin	
	Remember my credentials	
	ОК	Cancel

ขั้นตอนที่ 11: คลิ๊กบนแท็บของ SETUP แล้วเลือกปุ่ม Mail ที่อยู่ทางค้านซ้ายมือ ภายใต้ส่วนของ MAIL Account ตั้งค่าตามค้านล่าง

- 1. SMTP Server Address : ใส่ค่า smtp.gmail.com
- 2. SMTP Server Ports :465
- 3. Sender E-Mail Address : ใส่อีเมล์แอคเครสของ Gmail
- 4. Received E-Mail Address : ใส่อีเมล์แอดเดรของ Gmail
- 5. Username : ใส่บัญชี(เต็ม) ของ Gmail
- 6. Password : ใส่ค่ารหัสผ่านที่ใช้ในการเข้าถึงบัญชีผู้ใช้งานของ Gmail
- User SSL/TLS/STARTTLS : เถือกปุ่มเป็น SSL-TLS

Firmware version: 1.01

Product: DCS-933L

D-Link

933L	LIVE VIDEO	SETUP MA	INTENANCE	STATUS	HELP
d	MAIL				Helpful Hints
iork Setup	This section allows you to s	setup and configure the email	notification settin	gs for your camera. If	SMTP Server Address: This is the domain name or
less Setup	your details change or you modify these settings.	are experiencing issues with a	lert notifications,	you may need to	IP address of your external email server.
ender Setup	_				Sender F-mail Address:
namic DNS		Save Settings Don't	Save Settings		This is the email address of
age Setup	E-MAIL ACCOUNT				the person sending the camera snapshots.
eo	SMTP Server Address	smtp.gmail.com			Receiver E-mail
dio	SMTP Server Port	465	(Default	is 25)	Address: This is the email address of
tion Detection	Sender E-mail Address	bunsophil@gmail.com		10.00	recipient for the SMTP server.
and Detection	Receiver E-mail Address	bunsophil@gmail.com			User Name:
il ,	User Name	bunsophil@gmail.com			The user name of your email account.
P	Password				Password
me and Date	Use SSL-TLS/STARTTLS	No SSL-TLS STAR	TTLS		The password of your email account.
y/Night Mode		it and to car different different different different different different different different different differe	4.000		

ขั้นตอนที่ 12: ภายใต้ส่วนของ TIME SCHEDULE ทำเครื่องหมายเพื่อเลือกบน Enable emailing

images to an email account

TIME SCHEDULE
Enable the emailing of images to an email account
Always
Schedule
Day Mon Tue Wed Thu Fri Sat Sun Time Period Start : 00:00:00 (Example : 06:30:00) Stop : 00:00:00 (Example : 22:30:00)
 Motion/Sound Detection E-mail frame immediately E-mail attached with 6 frames (3 frames before and 3 frames after detection)
E-mail Interval 300 Seconds

ขั้นตอนที่ 13: คลิ๊กบนปุ่ม Save Setting เพื่อให้การตั้งค้ามีผล ภายใต้ส่วนของ TEST E-MAIL Account คลิ๊กบนปุ่ม Test เพื่อทดสอบการตั้งค่าอีเมล์แอดเดรสที่ตั้งค่าขึ้น



ขั้นตอนที่ 14: ข้อความจะปรากฏขึ้นเกี่ยวกับการตรวจสอบอุปกรณ์สำหรับการคสอบอีเมล์

REPLY MESSAGE
Test e-mail has been sent. Please check STATUS > Device Info menu to view success or failure of test e-mail.

ขั้นตอนที่ 15: คลิ๊กบนแท็บของ STATUS แล้วคลิ๊กเลือกปุ่ม Device Info ที่อยู่ทางค้านซ้ายมือ ภายใต้ส่วนของ BASIC INFORMATION คุณควรจะเห็นข้อความ Test Succeeded บน E-Mail Test Section อความจะปรากฏขึ้นเกี่ยวกับการตรวจสอบอุปกรณ์สำหรับการทดสอบอีเมล์ ซึ่งแสดงว่า email account กำลังทำงานอยู่



How to Configure the DCS-933L to Send E-mail Snapshots on Gmail Account

Step 1: Run the CD Set-Up that came with the DCS-933L. On the Set-Up Wizard screen click on **Set up your Could Camera** button.



Step 2: Click on Start button on the next window that comes up.



Step 3: Under End User License Agreement, put a check mark on **I accept these Terms and Conditions**, then click on **Next** button.

End User License	Agreement	^
IMPORTANT - READ	BEFORE COPYING, INSTALLING OR USING	=
HAVE CAREFULLY RE CORPORATION ("D-L FIRST ACCEPT THE AND/OR USING THE AGREEMENT. IF YOU AGREEMENT, PROMI LINK OR ITS AUTHOR RECEIVE A REFUND (EAD THE FOLLOWING TERMS AND CONDITIONS. D-LINK LINK") WILL LICENSE THE SOFTWARE TO YOU ONLY IF YOU TERMS OF THIS AGREEMENT. BY COPYING, INSTALLING SOFTWARE YOU AGREE TO THE TERMS OF THIS DO NOT WISH TO AGREE TO THE TERMS OF THIS PTLY RETURN THE UNUSED SOFTWARE TO THE PARTY (D- RIZED RESELLER) FROM WHOM YOU ACQUIRED IT TO OF THE AMOUNT YOU PAID.	
TL	cane the original coffware and all whole or partial conice of it. Software	-

Step 4: Plug the included Ethernet cable into the port on the back of the Cloud Camera, then Click on **Next** button to continue.



Step 5: Plug the other end of the cable into the LAN port on your router. Click **Next** button to continue.



Step 6: Connect the power adapter to the power connector on the back of the DCS-933L, then plug the adapter into a power outlet. Click **Next** button.



Step 7: The LED on the cloud camera will turn solid green when it is ready, Click Next button to proceed.

Connect your Cloud Camera	Connect 1 Network 2 Enable	0
Please follow these instructions to connect your Cl	ud camera.	
1. Cloud Camera	The LED on the Clo	bu
2. Router	green when it is read	iy.
3. Power adapter		
• 4. LED		
Click here to see a basic overview of how your devices connect together.	"What should I do if I LED stays red?	<u>he</u>
Back	Next	

Step 8: Click on the button **Yes** if the LED at the back of your camera is lit solid green.

-14-



Step 9: You will now see the camera device information with its corresponding IP Settings and MAC Address. Create a password for your camera then, Click on the **Next** button.

ect your	Cloud	Camera	Connect	1) Network (Enable Ena
Cloud C	amera	MAC ID 7	IP address	Conne	<u>cti</u> on
DCS-9: Searc	iaL hing Clou	28:10:78:09:C3:08 d Cameras	192.168.0.100		P)
 DCS-9: Searc Registered with 	th mydlink	28:10:78:09:C3:08 d Cameras Not red	192.168.0.100 gistered	Ired 9	P Wireless
Registered wi	hing Clou th mydlink Camera in the	28:10:78:09:C3:08 d Cameras Not reg	192.168.0.100 gistered Qr v Please enter a	Vired 9	Wireless
CCS-9: CCS-9:	hing Clou th mydlink Camera in the	28:10:78:09:C3:08 d Cameras Not rei	gistered V Please enter a Admin account: a	Ired I	Wireless ecure your came
Registered wi	BBL hing Clou th mydlink	28:10:78:09:C3:08 d Cameras Notre	gistered Please enter a Admin account: a Password:	Vired 9	P Wireless ecure your came

Step 10: Open up a browser and on the address bar type in the IP address of the camera, then Login page of the camera comes up. Type **"admin"** for username and type your password for your camera. Then click on **Log In** button.

http://192.168.0.100

Windows Security	
The server 192.168.0.100 at DC	S-933L requires a username and password.
Warning: This server is reques sent in an insecure manner (b connection).	ting that your username and password be asic authentication without a secure
admin	
Rememb	er my credentials
	OK Cancel

Step 11: Click on the **SETUP** tab and then select on **Mail** button on the left hand side. Under the **E-MAIL ACCOUNT** section, configure the following;

- 1. SMTP Server Address: Enter smtp.gmail.com
- 2. SMTP Server Port: 465
- 3. Sender E-mail Address: Enter the Gmail email address
- 4. Receiver E-mail Address: Enter the Gmail email address
- 5. User Name: Enter the complete Gmail username
- 6. **Password:** Enter the password to access the Gmail account
- 7. Use SSL-TLS/STARTTLS: Select the radio button on SSL-TLS

Product: DCS-933L					Firmware version: 1.01
D-Lin	K				\prec
DCS-933L	LIVE VIDEO	SETUP MAI	INTENANCE	STATUS	HELP
Wizard	MAIL				Helpful Hints
Network Setup	This section allows you to s	setup and configure the email r	notification settings	for your camera. If	SMTP Server Address: This is the domain name or
Wireless Setup	your details change or you modify these settings.	are experiencing issues with al	ert notifications, yo	ou may need to	IP address of your external email server.
Extender Setup	-				Sender E-mail Address:
Dynamic DNS		Save Settings Don't S	ave Settings		This is the email address of
Image Setup	E-MAIL ACCOUNT				the person sending the camera snapshots.
Video	SMTP Server Address	smtp.gmail.com			Receiver E-mail
Audio	SMTP Server Port	465	(Default is	; 25)	Address: This is the email address of
Motion Detection	Sender E-mail Address	bunsophil@gmail.com			recipient for the SMTP server.
Sound Detection	Receiver E-mail Address	bunsophil@gmail.com			User Name:
Mail	User Name	bunsophil@gmail.com			The user name of your email account.
FTP	Password				Password:
Time and Date	Use SSL-TLS/STARTTLS	No @ SSL-TLS @ START	TLS		The password of your email account.
Day/Night Mode			1		lise 551 -

Step 12: Under the **TIME SCHEDULE** section, put a check mark on **Enable emailing images to email account**.

TIME SCHEDULE	
Enable the emailing of images to an email account	
Always	
Schedule Day Mon Tue Wed Thu Fri Sat Sun Time Period Start : 00:00:00 (Example : 06:30:00) Stop : 00:00:00 (Example : 22:30:00)	
 Motion/Sound Detection E-mail frame immediately E-mail attached with 6 frames (3 frames before and 3 frames after detection) Frame interval time : 1 - second 	



TEST E-MAIL ACCOUNT	
A test e-mail will be sent to the e-mail account listed above.	2 Test
1 Save Settings Don't Save Settings	

Step 14: A message will appear saying to check the Device Info for the test e-mail account.



Step 15: Click on the **STATUS** tab and then select on **Device Info** button on the left hand side. Under the **BASIC INFORMATION** section, you should see a message "**Test succeeded**" on the Email Test section meaning that the e-mail account is working.

ฝ่ายสนับสนุนทางด้านเทคนิค

Call Center หมายเลขโทรศัพท์ 02-6617997

ภาษาไทย : จันทร์ ถึง ศุกร์ เวลา 9.00 น. – 18.00 น.

Thai : Mon - Fri : Time 9.00 - 18.00.

ภาษาอังกฤษ : เสาร์ , อาทิตย์ , วันหยุดนขัตฤกษ์ และ วันธรรมดา หลัง 18.00 น.

English : Sat - Sun , Public Holiday and after 18.00 weekday.

Website : www.dlink.co.th

email: <u>support@dlink.com.sg</u>

Facebook : http://www.facebook.com/DLinkThailandFans

-19-

Nationwide D-Link Service Centres

Chiang Mai Branch	Phitsanulok Branch
2/1 Moo 3, Chiang Mai-Lampang Road	117/7 Praongdam Road
Tumbon Chang Pueak, Amphoe Mueang Chiang Mai	Tumbon Nai Musang,
Changwat Chiang Mai 50300,	Amphoe Musang Phitsanulok
Thailand	Changwat Phitsanulok 65000, Thailand
Tel : +66 (0) 5340-9482-6	Tel I +66 (0) 9521-2323-5
Fax : +66 (0) 5340-9486	Fax I +66 (0) 9521-2326
Operating hours:	Operating hours:
Mondays till Friday	Mondays till Friday
9am to 6pm	9am to 6pm
Cham Issara Tower II	Panto Plaza Branch
3rd Floor, Cham Issara Tower II	4th FL Panto Plaza 604/3 Petchburi Ro-
2022/138 New Peychari Road	439-440

2922/138 New Perchburt Road Khwang Bangkapi, Khet Huay-Kwang, Bangkok 10320, Thailand

Tel: +66 (0) 2308-2040 Fax: +66 (0) 2308-2024 Call Center: +66 (0) 2716-6669 Operating hours: Mondays till Friday 9am to 6pm 4th FL Pantip Plaza 604/3 Petchburi Road Room 439-440 Kwang Thanon Petchburi, Khet Ratchathewi Bangkok 10400, Thailand Tel : +66 (0) 2656 6037 Tel : +66 (0) 2656 6054 Fax I +66 (0) 2656 6042 Operating hours: Mondays till Sunday 10am to 7pm

Rayong Branch

217/24 Sukhumvit Road Tursbon Noen Phra, Amphoe Musang Rayong Changwat Rayong 21000, Thailand

Tel : +66 (0) 3680-0631-3 Fax : +66 (0) 3880-0634 Operating hours: Mondays till Sunday 9am to 6pm

Surat Thani Branch

412/8 Talat Mai Road Tumbon Talat, Amphoe Mueang Surat Thani Changwat Surat Thani 84000, Thailand

Tel: +66 (0) 7721-7907-10 Fax: +66 (0) 7721-7910 Operating hours: Mondays till Friday 9am to 6pm

Phuket Branch

156/3 Phang Nga Road Tumbon Taratyai, Amphoe Mueang Phuket Changwat Phuket 83000, Thailand

Tel:+66 (0) 7623-2906-9 Fax:+66 (0) 7623-2909 Operating hours: Mondays till Friday 9am to 6pm

Hat Yai Branch

48/106 Phadungpakdee Road Tumbon Hatyai, Amphoe Hatyai Changwat Songkhla 90110, Thailand

Tel:+66 (0) 7435-4559-61 Fax:+66 (0) 7435-4561 Operating hours: Mondays till Friday 9am to 6pm