


Step 1 Connect Your PC (Laptop) to the Router (Port 1,2,3,4 either one of them) using Network cable.

Step 2 Launch your browser (Google Chrome) and key in 192.168.1.1 in the address column and press Enter




Step 3 Enter your Username: admin and Password: admin. Click on Log In



Step 4 You will see a D-Link configuration page, click on **Setup > Internet Setup > Internet Connection Type** and choose **Ethernet WAN (NBN/UFB)**.

Step 5 Choose the **Country > Malaysia** and **ISP > Maxis Fiber PPPoE**



Step 6

IPV4/IPV6: **IP Version > IPv4**

WAN Settings: **PPPOE**

Username: **Username provided by your ISP**

Password: **Password provided by your ISP**

WAN

Username:

Password:

Confirm Password:

MTU: (0:default)

TCP MSS: (0:default)

Default Route: ☒

NAT Enable: ☒

PPPoE UnNumbered: ☐

Enable PPPoE Passthrough: ☐

IGMP Proxy: ☐

Connection: ☒ Always On (Recommended)
☐ Connect On-Demand (Close if idle for minutes)
☐ Connect Manually

Get IP Address: ☐ Static ☒ Dynamic

Static IP Address:

IP Subnet Mask:

Gateway:

Step 7 Click > Apply. Plug in the cable into the DSL-2877AL **WAN Port**

Maxis IPTV Setup

Step 1 Click on **Internet Setup > Internet Connection Type** and choose **Ethernet WAN (NBN/UBF)**.

Step 2 Choose the **Service Num > 1**, **Enable Virtual Circuit > Tick**, **Country > Malaysia** and **ISP > Maxis Fiber IPTV**

DSL-2877AL // SETUP ADVANCED MAINTENANCE STATUS HELP

Wizard
Internet Setup
Wireless Setup
LAN Setup
3G/4G Setup
WAN Failover Priority Setup
Time and Date
IPv6RD
mylink™ Settings
Internet Offline
Reboot Logout

INTERNET SETUP

If you are configuring this device for the first time, we recommend that you click Setup Wizard button, and follow the instructions on screen.

MODE SELECT

Current WAN failover priority from high to low is DSL, Ethernet WAN, 3G/4G. If you want to change WAN priority, you can click SETUP>WAN Failover Priority Setup.

Internet Connection Type: Ethernet WAN (NBN/UBF)

ETH SETTING

Service Num: 1 Services Summary

Enable Virtual Circuit: ☒

Country: Malaysia

ISP: Maxis Fiber IPTV

802.1q: ☒ Activated ☐ Deactivated

VLAN ID: 823 (range: 0~4095)

IPV4/IPV6

IP Version: ☒ IPv4 ☐ IPv4/IPv6 ☐ IPv6

WAN SETTINGS

Configure your DSL connection here. Please consider the information of your provider on the settings otherwise it may not be possible to establish a connection.

☒ Dynamic IP Address Choose this option to obtain an IP address automatically from your ISP. (For most Cable modem users)

☐ Static IP Address Choose this option to set static IP information provided to you by your ISP.

☐ PPPoE Choose this option if your ISP uses PPPoE. (For most DSL users)

Helpful Hints...

If you are the first time use this device, we recommend you to run the wizard. It will guide you step by step.

Here you can quickly setup your WAN connection. These details should have been provided by your ISP (Internet Service Provider). Often you will receive a bundle pack with the important account information.

Very often in the United Kingdom User will require to PPPoA connection type. Users in Germany should select PPPoE when applicable. Please be careful with the username and password. They are case sensitive. For most users, if you are unable to connect it, your username and password combination may be incorrect.

More...

Step 3

IPV4/IPV6: **IP Version > IPv4**

WAN Settings: **Dynamic IP Address**

IGMP Proxy: **Tick**

WAN

MTU: 1500 (0:default)

Default Route: ☐

NAT Enable: ☐

Enable PPPoE Passthrough: ☐

IGMP Proxy: ☒

Apply

Step 4 Click > **Apply**. Plug in the **IPTV LAN Cable** into the **DSL-2877AL ANY LAN Port**