

วิธีการเปิดใช้ DDNS บน	<b>DCS-930L</b>
------------------------	-----------------

ขั้นตอนที่ 1: คลิกปุ่ม Start บนคอมพิวเตอร์ของคุณและจากนั้นเลือก All Programs



ขั้นตอนที่ 2: ภายใต้โปรแกรมทั้งหมดที่เลือกบน D - Link> Setup Wizard SEและจากนั้นคลิกเกี่ยวกับ D - Link Setup Wizard SE

a Internet	🛐 Outlook Express	
Internet Explor	🔁 Remote Assistance	pote A
E-mail	📀 Windows Media Player	
Microsoft Office	🔏 Windows Messenger	
<b>~</b>	🚳 Windows Movie Maker	
	📐 Adobe Reader 9	
	🛅 K-Lite Codec Pack	
	m SnagIt 8	
	🛅 Bullzip	
	🛅 FileZilla FTP Client	
l otus Notes	C WinRAR	▶ nd
	Windows Live	
	Boxee 1	) Z ,
	🖬 D-Link	▶
Adobe Reader 9	PHP 5	Installation Wizard     Mizard     Mizard     Mizard
	Zoom Search Engine 6.0	
	TeamViewer 6	
	WinPcap	
All Deserves A	Wireshark	
All <u>P</u> rograms	Mitel	
	🖉 Log Off 🛛 🗿 Turn	Off Computer
🛃 Start 🕓 Inbox - M	Microsoft Outl 🥻 🏉 D-LINK CORPOR	ATIO 🔗 DRS Escalation Datab 📔 🗁 DriveD

ขั้นตอนที่ 3: เกี่ยวกับตัวช่วยสร้างการติดตั้ง D - Link, กล้องที่คุณต้องการในการเข้าถึงและแล้วคลิกที่ปุ่มการเชื่อมโยง

D-Link Eulding Networks for People					
2 Link About Exit	1 MAC Address 1 1 1 1 10.7d.68.05.30.cb	Current IP Address 192.168.100.23	Device Name DCS-930L		

**ขั้นตอนที่ 4:** จากหน้าต่างล็อคอินให้ใส่ค่า username เป็น "**admin**" แล้วรหัสผ่านที่ใช้ในการเมื่อคุณเรียกใช้ตัวช่วยสร้าง คลิกปุ่ม OK



## **ขั้นตอนที่** 5: คลิกที่แท็ป SETUPและเลือกไปที่ปุ่ม Dynamic DNS ทางด้านซ้ายมือ ภายใต้ DYNAMIC DNS SETINGS ให้ตั้งค่าดังต่อไปนี้

เลือกปุ่มตัวเลือกเกี่ยวกับการเปิดใช้งาน
 เลือกเซิร์ฟเวอร์ DDNS ที่คุณได้ลงทะเบียน
 ป้อนชื่อโฮสต์ที่ใช้เมื่อคุณได้ลงทะเบียนเพื่อ DDNS
 ป้อนชื่อผู้ใช้ที่ใช้ในการเข้าระบบไปยังเซิร์ฟเวอร์ DDNS
 ป้อนรหัสผ่านที่ใช้ในการเข้าระบบไปยังเซิร์ฟเวอร์ DDNS
 6 กลิกที่ปุ่ม Save Settings

Product: DCS-930L					
<b>D-Lin</b> l	K				
DCS-930L	LIVE VIDEO	SETUP	1	MAINTENANCE	STATUS
Wizard	DYNAMIC DNS				
Network Setup	The Dynamic DNS feat	ture allows you to ho	st a se	erver (Web, FTP, Camera,	etc) using a domain
Wireless Setup	name that you have purchased (www.whateveryournameis.com) from your broadband Internet Service Provider (ISP). Using a DDNS service, your friends can enter your host name to connect				
Dynamic DNS <b>2</b>	to your IP Camera reg	ardless of your IP add	dress.		
Image Setup		Save Settings		Don't Save Settings	
Video					
Audio	DYNAMIC DNS SE	TING			
Motion Detection	3 © Enable O Disable	•			
Mail	Server Address	w.dlinkddns.com		< www.dlinkddns.com	- 4
FTP	Host Name dlink	123.dlinkddns.com		5	
Time and Date	User Name jess	ber		6	
Logout	Password	•••		7	
	Timeout 576			hours	
	8	Save Settings		Don't Save Settings	



## How to Enable DDNS on DCS-930L

Step 1: Click on the Start button on your computer and then select on All Programs.



Step 2: Under the All Programs select on D-Link > Setup Wizard SE and then click on D-Link Setup Wizard SE button.



**Step 3:** On the *D-Link Setup Wizard*, the camera you want to access and then click on the Link button.

D-Link Building Networks for People					
Wizard Search 2 Link About Exit	1 MAC Address 1 1 10.7d.68.05.30.cb	Current IP Address           192.168.100.23           -	Device Name DCS-930L		

**Step 4:** A login screen will appear, enter the username as "**admin**" and then the password used to when you run the wizard. Click on **OK** button.

Connect to 192.168	3.100.23	<u>?</u> ×			
		G			
The server 192.168.100.23 at DCS-930L requires a username and password. Warning: This server is requesting that your username and password be sent in an insecure manner (basic authentication without a secure connection).					
User name: Password:	🖸 admin	<b></b>			
Remember my password					
OK Cancel					

**Step 5:** Click on the **SETUP** tab on top and then click on the **Dynamic DNS** on the Left Hand Side. Under the **DYNAMIC DNS SETINGS** configure the following;

- 1. Select the radio button on Enable
- 2. Select the DDNS Server where you've registered
- 3. Enter the Host Name used when you've registered to a DDNS
- Enter the Username used to login to the DDNS Server
   Enter the Password used to login to the DDNS Server
   Click on the Save Settings button

Product: DCS-930L						
D-Lin	C					
DCS-930L	LIVE VIDEO	SETUP <b>1</b>	MAINTENANCE	STATUS		
Wizard	DYNAMIC DNS					
Network Setup	The Dynamic DNS feat	ure allows you to host a s	erver (Web, FTP, Camera,	etc) using a domain		
Wireless Setup	name that you have purchased (www.whateveryournameis.com) from your broadband Internet Service Provider (ISP). Using a DDNS service, your friends can enter your host name to connect					
Dynamic DNS <b>2</b>	to your IP Camera rega	ardless of your IP address.				
Image Setup		Save Settings	Don't Save Settings			
Video						
Audio	DYNAMIC DNS SETTING					
Motion Detection	3					
Mail	Server Address	v.dlinkddns.com	<pre> &lt;&lt; www.dlinkddns.com</pre>	<u> </u>		
FTP	Host Name dlink:	123.dlinkddns.com	5			
Time and Date	User Name jessp	er	6			
Logout	Password .	•••	7			
	Timeout 576		hours			
	8	Save Settings	Don't Save Settings			