

FAQ : How to Perform a Firmware Upgrade on the DCS-930L

Release date : 6/02/2012

Model Support : DCS-930L

H/W:A1

S/W:1.00

วิธีที่จะทำการอัพเกรดเฟิร์มแวร์บน \mathbf{DCS} -930 $\mathbf L$

ขั้นตอนที่ 1: คลิกปุ่ม Start บนคอมพิวเตอร์ของคุณและจากนั้นเลือก All Programs



ขั้นตอนที่ 2: ภายใต้โปรแกรมทั้งหมดที่เลือกบน D - Link> Setup Wizard SEและจากนั้นคลิกเกี่ยวกับ D - Link Setup Wizard SE

Internet	🗿 Outlook Express			
	💫 Remote Assistance	ents 🕨		
E-mail Microsoft Office	🕑 🛛 Windows Media Player			
, microsore ornee	🔏 Windows Messenger			
Notopad	🕸 Windows Movie Maker			
	😕 Adobe Reader 9			
	🛅 K-Lite Codec Pack	▶		
	🛅 SnagIt 8	▶		
	🛅 Bullzip	▶		
	🛅 FileZilla FTP Client	▶		
🕢 Lotus Notes	m WinRAR	▶ _{bd}		
	🛅 Windows Live			
	m Boxee 1	2		
	📅 D-Link	Setup Wizard SE D-Link Setup Wizard SE		
	PHP 5	🕨 🛅 Installation Wizard 🕩 🛃 Uninstall Setup Wizard SE		
	Zoom Search Engine 6.0			
	TeamViewer 6			
	🛅 WinPcap			
	Wireshark			
All Programs	m Mitel			
Log Off 🛛 Off Computer				
🛃 Start 🛛 🙆 Inbox - M	icrosoft Outl 🦽 D-LINK CORPORA	IO 🚱 DRS Escalation Datab 🔀 DriveD		

FAQ : How to Perform a Firmware Upgrade on the DCS-930LAccountVersion 1.00



ขั้นตอนที่ 3: เกี่ยวกับตัวช่วยสร้างการติดตั้ง D - Link, กล้องที่คุณต้องการในการเข้าถึงและแล้วคลิกที่ปุ่มการเชื่อมโยง

D-Link Building Networks for People	esec	URICAM Network	
2 Link About Exit	1 MAC Address 1 10.7d.68.05.30.cb	Current IP Address 192.168.100.23	Device Name DCS-930L

ขั้นตอนที่ 4: จากหน้าต่างล็อคอินให้ใส่ค่า username เป็น "**admin**" แล้วรหัสผ่านที่ใช้ในการเมื่อคุณเรียกใช้ตัวช่วยสร้าง คลิกปุ่ม OK



FAQ : How to Perform a Firmware Upgrade on the DCS-930LAccountVersion 1.00

D-Link

ขั้นตอนที่ 5: คลิกที่แท็ป MAINTENANCE และเลือกไปที่ปุ่ม Firmware Upgrade ทางด้านซ้ายมือ

Product: DCS-930L					
	C				
DCS-930L	LIVE VIDEO	SETUP	MAINTENANCE	STATUS	
Admin	FIRMWARE UPGRADE				
System	A new firmware upgrade may be available for your camera. It is recommended to keep your				
Firmware Upgrade	camera firmware up-to-date to maintain and improve the functionality and performance of your internet camera. Click here <u>D-Link Support Page</u> to check for the latest firmware version				
Logout	available.				
	To upgrade the firmwa version from the D-Link drive by clicking the Bro button, click the Uploa	are on your IP camera, ple c Support Page to your lo owse button. Once you h ad button to start the firm	ease download and save the cal hard drive. Locate the f nave found and opened the mware upgrade.	e latest firmware île on your local hard e file using the browse	

ขั้นตอนที่ 6: ภายใต้ส่วน *FIRMWARE UPGRADE* ให้กลิกที่ปุ่ม Browse

FIRMWARE INFORMAT	ION	
Current Firmware Version : Current Firmware Date :	1.01 2011-07-28	
FIRMWARE UPGRADE		
File Path :	Upload	Browse

ขั้นตอนที่ 7: ภายใต้การเลือกไฟล์ที่ต้องการอัพโหลดให้ค้นหาและเลือกไฟล์เฟิร์มแวร์สำหรับ DCS-932L แล้วคลิกที่ปุ่ม Open

Choose File to Up	oload				? ×
Look in:	📄 Firmware		•	G 👂 📂 🖪	•
My Recent Documents Desktop My Documents My Computer	DCS-930L				
My Network	, File name:	DCS-930L		•	Open
Places	Files of type:	All Files (*.*)		•	Cancel

ขั้นตอนที่ 8: กลับไปที่ FIRMWARE UPGRADE ให้คลิกที่ปุ่ม

FIRMWARE INFORMATION				
Current Firmware Version : Current Firmware Date :	1.01 2011-07-28			
FIRMWARE UPGRADE				
File Path :	C:\Documents and Settings\Jessper\Desk	Browse		



How to Perform a Firmware Upgrade on the DCS-930L

Step 1: Click on the Start button on your computer and then select on All Programs.



Step 2: Under the All Programs select on D-Link > Setup Wizard SE and then click on D-Link Setup Wizard SE button.

Internet	🗐 Outlook Express			
	💫 Remote Assistance	ents >		
E-mail Microsoft Office	🕑 Windows Media Player			
	🔏 Windows Messenger			
	🚳 Windows Movie Maker			
Motepau	😕 Adobe Reader 9			
Microsoft Office	🛅 K-Lite Codec Pack			
	SnagIt 8			
	🛅 Bullzip	→		
	🛅 FileZilla FTP Client	→ · · · · · · · · · · · · · · · · · ·		
🔊 Latus Notes	m WinRAR	→ _{bd}		
	🛅 Windows Live			
	Boxee 1	2		
	🖬 D-Link	🕨 🖮 Setup Wizard SE 🔹 🚺 D-Link Setup Wizard SE 3		
Adobe Reader 9	m PHP 5	🕨 🛅 Installation Wizard 🔸 🛃 Uninstall Setup Wizard SE		
	Zoom Search Engine 6.0			
	TeamViewer 6	- • I		
	im WinPcap			
All Due success	Wireshark			
All <u>P</u> rograms	m Mitel			
Log Off 🛛 💽 Tyrn Off Computer				
🛃 Start 🕓 Inbox - M	/icrosoft Outl 🥻 🄏 D-LINK CORPOR	ATIO 🙆 DRS Escalation Datab 📄 DriveD		

FAQ : How to Perform a Firmware Upgrade on the DCS-930LAccountVersion 1.00



Step 3: On the *D-Link Setup Wizard*, the camera you want to access and then click on the Link button.

D-Link Euliding Network				
2 Link About Exit	1 MAC Address 1 1.7d.68.05.30.cb	Current IP Address 192.168.100.23	Device Name DCS-930L	

Step 4: A login screen will appear, enter the username as "**admin**" and then the password used to when you run the wizard. Click on **OK** button.

Connect to 192.16	68.100.23	<u>? ×</u>		
		G P		
The server 192.160 and password. Warning: This serv password be sent i without a secure co	8.100.23 at DCS-930L er is requesting that y n an insecure manner onnection).	, requires a username your username and (basic authentication		
User name:	🖸 admin	•		
Password:	•••••			
	🗖 Remember my	password		
	ок	Cancel		

Step 5: Click on the **MAINTENANCE** tab and then select on **Firmware Upgrade** button on the left hand side.



Step 6: Under the FIRMWARE UPGRADE section, click on the Browse button.

ON	
1.01 2011-07-28	
Upload	Browse
	1.01 2011-07-28 Upload

Step 7: Under the Choose File to Upload dialog box, locate and select the firmware file for the DCS-932L and then click on **Open** button

Choose File to L	Ipload				<u>? ×</u>
Look in	: 🗀 Firmware		• 6) 🤣 📂 🖽	•
My Recent Documents Desktop My Documents My Computer	DCS-930L				
My Network	File name:	DCS-930L		•	Open
Places	Files of type:	All Files (*.*)		•	Cancel

Step 8: Back on the FIRMWARE UPGRADE dialog box, click on the **Upload** button.

FIRMWARE INFORMATION			
Current Firmware Version : Current Firmware Date :	1.01 2011-07-28		
FIRMWARE UPGRADE			
File Path :	C:\Documents and Settings\Jessper\Desk	Browse	