How to setup High Speed Broadband for Malaysia (TM Unifi / Maxis fibre Home) For DIR-850L.

Step 1 Connect Your PC (Laptop) to the Router (Port 1,2,3,4 either one of them) using Network cable.

Step 2 Launch your IE (Internet explorer) and key in 192.168.0.1 in the address column and press Enter.



Step 3 Enter your Username: admin and no password (if it is default) click on Log In

LOGIN	
Log in to the router	User Name : Admin Password : Log In

Step 4 You will see a D-Link configuration page, click on Setup > Internet > Manual Internet Connection Setup.

//	SETUP	ADVANCED	TOOLS	STATUS		
INTERNET	INTERNET CONNECTION					
WIRELESS SETTINGS	There are two ways to	set up your Internet cor	nnection: you can use the	Web-based Internet		
NETWORK SETTINGS	Connection Setup Wizard, or you can manually configure the connection.					
STORAGE						
IPV6	INTERNET CONNECT	TION SETUP WIZARD)			
MYDLINK SETTINGS	If you would like to util new D-Link Systems Ro	ize our easy to use Web- outer to the Internet, clic	based Wizards to assist yo k on the button below.	u in connecting your		
	Note: Before bunching the Quick Installation G	these wizards, please m uide included in the pack	ake sure you have followe age.	d all steps outlined in		
	MANUAL INTERNET	CONNECTION OPTIC	ons			
	If you would like to con then click on the butto	nfigure the Internet setti n below.	ngs of your new D-Link Sy	stems Router manually,		
		Manual Internet (Connection Setup			

Step 5 For My Internet Connection select Unifi-PPPoE (Username / Password)

INTERNET CONNECTION TYPE			
Choose the mode to be used by	the router to connect to the Internet.		
My Internet Connection is	Unifi-PPPoE (Username / Password)		
Disable NAT :			

Step 6

Address Mode: Dynamic IP Username: Username provided by your ISP Password: Password provided by your ISP

Address Mode	Dynamic IP Static IP
IP Address :	
Username :	test1@unifi
Password :	
Verify Password :	
Service Name :	(optional)
Reconnect Mode :	Always
	On demand
Maximum Idle Time :	5 (minutes, 0=infinite)
DNS Mode :	Receive DNS from ISP Enter DNS Manually
Primary DNS Server :	
Secondary DNS Server :	(optional)
MTU :	1492
MAC Address :	

Step 7 Under VLAN Bridge, please enter the internet VLAN ID and IPTV VLAN ID, please check with your ISP for your VLAN ID

For Malaysia

TM Unifi	ID No.	Maxis	ID No.
Internet VLAN ID	500	Internet VLAN ID	621
IPTV VLAN ID	600	IPTV VLAN ID	823

VLAN BRIDGE	
Internet VLan ID : 500 IPTV VLan ID : 600	
VoIP VLan ID: 400	
Interface	WAN Connection
LAN Port 1	Internet 💌
LAN Port 2	Internet 💌
LAN Port 3	Internet 🔻
LAN Port 4	IPTV 🔻

Step 8 Click on Save setting to complete internet setup.

