

TM Streamyx Setup

Step 1 Connect Your PC (Laptop) to the Router (Port 1,2,3,4 either one of them) using Network cable.

Step 2 Launch your browser (Google Chrome) and key in 192.168.1.1 in the address column and press Enter



Step 3 Enter your Username: admin and Password: admin. Click on Log In

A screenshot of the D-Link router login page. The page has an orange header with the "D-Link" logo. Below the header is a "LOGIN" section with a light gray background. It contains the text "Login in to the router" and two input fields labeled "Username :" and "Password :". A "Login" button is positioned below the password field. At the bottom of the page, there is a dark gray bar with the word "BROADBAND" in white capital letters.

Step 4 You will see a D-Link setup wizard page, click on **Next**.

A screenshot of the D-Link setup wizard welcome page. The page has an orange header with the "D-Link" logo. Below the header is a "WELCOME TO THE SETUP WIZARD" section with a light gray background. It contains the text "Welcome to the Setup Wizard:" followed by a bulleted list of seven steps: Step 1: Set your password, Step 2: Select your Time Zone, Step 3: Configure your internet connection, Step 4: Name your Wireless Network, Step 5: Secure your Wireless Network, Step 6: Set your Wireless Security Password, and Step 7: Setup mydlink™ Cloud Services. At the bottom of the section are four buttons: "Prev", "Next", "Cancel", and "Connect". At the bottom of the page, there is a dark gray bar with the word "BROADBAND" in white capital letters.

Step 5 Choose your device **Password**, click on **Next**.



STEP 1: SET YOUR PASSWORD

To secure your new networking device, please set and verify a password below:

Password :

Verify Password :



Step 6 Choose your device **Time Zone** to GMT+8, click on **Next**.



STEP 2: SELECT YOUR TIME ZONE

Select the appropriate time zone for your location. This information is required to configure the time-based options for the router.

Time Zone:



Step 7 Choose the following, and click **Next**.

Internet Connection Type : **ADSL**
Country : **Malaysia**
Internet Service Provider : **Choose your ISP (Streamyx PPPoE or etc)**
Protocol : **PPPoE (Or PPPoA dependent on your selection)**
Connection Type : **LLC**
VPI : **0**
VCI : **35**
MTU : **1492**

Product Page : DSL-2877AL Firmware Version : 1.00.15SE

D-Link

STEP 3: CONFIGURE YOUR INTERNET CONNECTION

Please select your Interface and Protocol from the list below.

Internet Connection Type : ADSL
Country : Malaysia
Internet Service Provider : (Click to Select)

Prev Next C

Maxis (Maxis PPPoA)
Maxis (Maxis PPPoE)
Streamyx (Telecom Malaysia - PPPoE)
Streamyx (Telecom Malaysia - PPPoA)
Time
Others

BROADBAND

Step 8 Choose the following, and click **Next**.

Username : **Username provided by your ISP**
Password : **Password provided by your ISP**
Confirm Password : **Password provided by your ISP**

SET PPPOE

Enter the PPPoE information provided to you by your ISP. Click Next to continue.

User Name : user@streamyx
Password :
Confirm Password :

Prev Next Cancel Connect

Step 9 Fill in the following, and click **Next**.

2.4G Wireless SSID : **2.4G Wireless Name**

5G Wireless SSID : **5G Wireless Name**

STEP 4: NAME YOUR WIRELESS NETWORK

Your wireless network needs a name so it can be easily recognised by wireless clients. For security purpose, it is highly recommended to change the default pre-configured network name.

2.4G Wireless Network Name (SSID) :

5G Wireless Network Name (SSID) :

Step 8 Choose the following, and click **Next**.

BEST : **WPA2 (Preferred Security)**

Better : **WPA**

Good : **WPE**

None : **No security**

STEP 5: SECURE YOUR WIRELESS NETWORK

In order to protect your network from hackers and unauthorized users, it is highly recommended you choose one of the following wireless network security settings.

There are three levels of wireless security - Good Security, Better Security, or Best Security. The level you choose depends on the security features your wireless adapters support.

For information on which security features your wireless adapters support, please refer to the adapters' documentation.

Note: All wireless adapters currently support WPA

BEST : ☒ Select this option if your wireless adapters SUPPORT WPA2

BETTER : ☐ Select this option if your wireless adapters SUPPORT WPA

GOOD : ☐ Select this option if your wireless adapters DO NOT SUPPORT WPA

NONE : ☐ Select this option if your do not want to activate any security features

Step 9 Fill in the following, and click **Next**.to continue mydlink setup or Click **Connect** to skip mydlink setup.

2.4G Wireless Security Password : **2.4G Wireless Security Password**

5G Wireless Security Password : **5G Wireless Security Password**

STEP 6: SET YOUR WIRELESS SECURITY PASSWORD

Once you have selected your security level - you will need to set a wireless security password. With this password, a unique security key will be generated.

2.4G Wireless Security Password :

5G Wireless Security Password :